PA29F-S4-TS Data Sheet 48 pin TSOP Socket/32 pin DIP 0.6" plug


Supported Device/Footprints

This adapter converts the AMD 29Fx00 in its 48 pin TSOP package to a 32 pin DIP programming footprint for the Dataman S4 programmer.


	Socket		Footprint	
Manufacturer	Device	Package	Device	Plug
AMD	29F200	48 TSOP	29F200	32 DIP
"	29F400	"	29F400	"

The TSOP socket has been changed by its manufacturer. In the past it accepted devices Live Bug or Dead Bug. Now it only accepts devices Live Bug.

The adapter accepts packages with the dimensions listed below:



Adapter Dimensions



Known Programmer Compatibility

· · ·				
The following compatibility information has been reported to Logical Systems.				
Programmer	Status			
Dataman: S4	Works			
DeviceRama: ChipBurner 8; CBU-40; CBU-48;	Not Compatible			
EasyWriter Portable				
EE Tools: AllMax, MegaMax; TopMax	Not Compatible			

The 29Fx00 is a superset of the 29F0x0. The 29Fx00 can be accessed in byte mode as the 29F0x0 is. This similarity allows a programmer that supports the 29F0x0 to offer support for the 29Fx00.

The Sector Operations are different for 29Fx00 and 29F0x0 devices. They also vary among device manufacturers. If the device programmer incorporates Sector Operations in its erase or programming operations, there will be compatibility issues.

Therefore, the programmer must offer a 29Fx00 menu selection or must otherwise be known to support the 29F0x0. Compatibility is NOT guaranteed by this adapter alone.



Adapter Construction

The adapter is made up of 3 sub-assemblies. They assemble via connectors making the adapter modular. This way the sub-assemblies can be replaced easily.

The following chart lists the adapter described by this datasheet and its subassembly.

Adapter	Socket	Top Board	Bottom Board
PA29F-S4-TS	48TSJ-W20	48TS29F	29F-S4

Test Sockets

LSC #	Style Mfgr/Pn	
48TSJ-W20	Open Top	Wells /648-0482211SA01

When disassembling the adapter take care not to bend the pins. When reassembling the adapter note the pin 1 indicators to align the parts correctly.

This adapter has also been offered as
PA29F-TS.
The two adapters are the same and the other
part number is being discontinued.

Adapter Wiring

TSOP	DIP	DIP	TSOP
device	plug	plug	device
1	2	30	48
2	3	16	47
	39	2 16	46
_	48	2 12	45
5	4	21	44
	65	2 NC	43
	73	2 20	42
	86	2 NC	41
	9 C	N 19	40
10	NC	NC	39
11	31	18	38
12	32	32	37
13	NC	NC	36
14	NC	17	35
15	NC	NC	34
16	NC	15	33
17	1	NC	32
18	27	14	31
19	5	NC	30
20	6	13	29
21	7	24	28
22	8	16	27
23	9	22	26
24	10	11	25

PA29F-S4-TS Data Sheet Doc: 29FS4-TS.DOC Rev 04/10/00 Page 1 of 1